



**REVERSE VOLTAGE – 100 Volts** 

# LITE-ON SEMICONDUCTOR

## SURFACE-MOUNT FAST SWITCHING DIODE

### FEATURES

- Fast switching speed
- · Ideally suited for automatic insertion
- For general purpose switching applications
- Lead-Free Finish; RoHS Compliant (Notes 1 & 2)
  Halogen and Antimony Free. "Green" Device

### **MECHANICAL DATA**

(Note 3)

- Package: SOD-123 plastic
- Package Material: "Green" molding compound, UL flammability classification 94V-0, (No Br. Sb. Cl.), "Halogen-free"
- Moisture Sensitivity: Level 1 per J-STD-020
- Lead free in RoHS 2002/95/EC compliant
- Weight: 11.67mg (Approximate)

MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS Ratings at +25°C ambient temperature unless otherwise specified.

PARAMETER		SYMBOL	VALUE	UNIT
Non-repetitive peak reverse voltage		V <sub>RM</sub>	100	V
Repetitive peak reverse voltage Working peak reverse voltage DC blocking voltage		V <sub>RRM</sub> V <sub>RWM</sub> V <sub>R</sub>	100	V
Forward continuous current		I <sub>FM</sub>	300	mA
Average rectified output current		Ιo	150	mA
Non-repetitive peak forward current @ t = 1us		I <sub>FSM</sub>	2	A
Repetitive peak forward current		I <sub>FRM</sub>	300	mA
Power dissipation		PD	400	mW
Operation temperature range	$\sim \sim \sim$	TJ	+150	°C
Storage temperature range		T <sub>STG</sub>	-65 to +150	°C
TATIC ELECTRICAL CHARACT	ERISTICS			
PARAMETER	TEST CONDITION	SYMBOL	MAX	UNIT
Forward voltage	= 1mA = 10mA = 50mA	V <sub>F</sub>	715 855 1000 1250	mV
	= 150mA			
Reverse leakage current	= 150mA = 75V = 20V	I <sub>R</sub>	2500 25	nA
Reverse leakage current V <sub>R</sub> V <sub>R</sub>	= 75V	I <sub>R</sub> C <sub>D</sub>	2500	nA pF
Reverse leakage current     V <sub>R</sub> Typical junction capacitance     V <sub>R</sub>	= 75V = 20V		2500 25	
Reverse leakage current V <sub>R</sub> V <sub>R</sub>	= 75V = 20V = 0V, f = 1MHz		2500 25	

### DYNAMIC ELECTRICAL CHARACTERISTICS

PARAMETER	TEST CONDITION	SYMBOL	TYP.	UNIT
Reverse recovery time	$I_F = 0.5A, I_{rr} = 0.25A, I_R = 1.0A$	t <sub>rr</sub>	4	ns

#### Notes:


1. EU Directive 2002/95/EC (RoHS), 2011/65/EU (RoHS 2) & 2015/863/EU (RoHS 3) compliant. All applicable RoHS exemptions applied.

2. See https://www.diodes.com/quality/lead-free/ for more information about Diodes Incorporated's definitions of Halogen- and Antimony-free, "Green" and Lead-free.

3. Halogen- and Antimony-free "Green" products are defined as those which contain <900ppm bromine, <900ppm chlorine (<1500ppm total Br + Cl) and <1000ppm antimony compounds.


## SOD-123 Plastic

FORWARD CURRENT – 0.15 Amperes





## LITE-ON SEMICONDUCTOR





## LITE-ON SEMICONDUCTOR

# **Ordering Information:** Packing **Part Number** Package Qty. Carrier Tape & Reel 1N4148W SOD-123 Plastic 3000pcs **Marking Information: Product Type** Marking Code Marking Code **Device P/N Pin Diagram** Equivalent Circuit Diagram 1 1N4148W Τ4 1 0-**-0** 2 2



## LITE-ON SEMICONDUCTOR

### IMPORTANT NOTICE

1. DIODES INCORPORATED (Diodes) AND ITS SUBSIDIARIES MAKE NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO ANY INFORMATION CONTAINED IN THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

2. The Information contained herein is for informational purpose only and is provided only to illustrate the operation of Diodes' products described herein and application examples. Diodes does not assume any liability arising out of the application or use of this document or any product described herein. This document is intended for skilled and technically trained engineering customers and users who design with Diodes' products. Diodes' products may be used to facilitate safety-related applications; however, in all instances customers and users are responsible for (a) selecting the appropriate Diodes products for their applications, (b) evaluating the suitability of Diodes' products for their intended applications, (c) ensuring their applications, which incorporate Diodes' products, comply the applicable legal and regulatory requirements as well as safety and functional-safety related standards, and (d) ensuring they design with appropriate safeguards (including testing, validation, quality control techniques, redundancy, malfunction prevention, and appropriate treatment for aging degradation) to minimize the risks associated with their applications.

3. Diodes assumes no liability for any application-related information, support, assistance or feedback that may be provided by Diodes from time to time. Any customer or user of this document or products described herein will assume all risks and liabilities associated with such use, and will hold Diodes and all companies whose products are represented herein or on Diodes' websites, harmless against all damages and liabilities.

4. Products described herein may be covered by one or more United States, international or foreign patents and pending patent applications. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks and trademark applications. Diodes does not convey any license under any of its intellectual property rights or the rights of any third parties (including third parties whose products and services may be described in this document or on Diodes' website) under this document.

Standard Terms 5 Diodes' products are provided subject to Diodes' and Conditions of Sale (https://www.diodes.com/about/company/terms-and-conditions/terms-and-conditions-of-sales/) or other applicable terms. This document does not alter or expand the applicable warranties provided by Diodes. Diodes does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel.

6. Diodes' products and technology may not be used for or incorporated into any products or systems whose manufacture, use or sale is prohibited under any applicable laws and regulations. Should customers or users use Diodes' products in contravention of any applicable laws or regulations, or for any unintended or unauthorized application, customers and users will (a) be solely responsible for any damages, losses or penalties arising in connection therewith or as a result thereof, and (b) indemnify and hold Diodes and its representatives and agents harmless against any and all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim relating to any noncompliance with the applicable laws and regulations, as well as any unintended or unauthorized application.

7. While efforts have been made to ensure the information contained in this document is accurate, complete and current, it may contain technical inaccuracies, omissions and typographical errors. Diodes does not warrant that information contained in this document is error-free and Diodes is under no obligation to update or otherwise correct this information. Notwithstanding the foregoing, Diodes reserves the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes.

8. Any unauthorized copying, modification, distribution, transmission, display or other use of this document (or any portion hereof) is prohibited. Diodes assumes no responsibility for any losses incurred by the customers or users or any third parties arising from any such unauthorized use.

9. This Notice may be periodically updated with the most recent version available at <u>https://www.diodes.com/about/company/</u> terms-and-conditions/important-notice

The Diodes logo is a registered trademark of Diodes Incorporated in the United States and other countries. All other trademarks are the property of their respective owners. © 2023 Diodes Incorporated. All Rights Reserved.

www.diodes.com